



DC SER1

PCI 32 bit P&P
1S (16C650 32FIFO)

Hardware Guide

DESCRIPTION:

The DC SER1 32Bit PCI bus Plug & Play 1S I/O card is equipped with two High-Speed RS-232.V24 Standard Serial-Interface, The serial port include 32 Byte FIFO, The speed Up to 921Kb/Sec. The DC SER1 include two 9 pin male connector for attaching peripheral's unit with Serial RS-232 Standard Interface.

Check your packing listing:

DC SER1 Card
Software Driver
Hardware Guide

Hardware Specification

Serial Port:

UART Chipset: SUN1889, Hardware FIFO are 32Byte FIFO,

Compatible chips: with 16C650, 16C550 and 16C450.

IEEE standard: RS-232 Interface

Driver Chipset: TI-75232, speed up to 100Kb/Sec, length 300-500M.

Max. Speed: Up to 921Kb/Sec (HYPER Terminor program)

Hardware installation guide:

- Turn off the power of your computer*
- Plug-in the DC SER1 MIO Series Adapter to PCI bus of your computer*
- Add-on the peripheral (Printer, Modem, Scanner... etc.) that you need to this Adapter*
- Turn on the power of your computer*

PCI device listing display (for example...)

Bus No	Device No	Func No	Vendor ID	Device ID	Device Class	IRQ
0	7	1	8086	7010	IDE Controller	14
0	13	0	1409	7168	Simple COMM. Controller	10

✍ After The Screen, your Card install correct, you can install WINDOWS 95,98,NT, 2000 or LINUX, Please see INSTALL GUIDE

When Display Vendor ID, Device Id, Device Class or IRQ aren't DISPLAY or ERROR value, Please

- . Change other slot
- . Clean your slot
- . Change other slot
- . Clean DC SER1 golden finger
- . Return DC SER1 card to manufacture

✍ ***PIN ASSIGNMENTS:***

Serial 9 Pin male connector pin assignments:

Serial 9 Pin male connector (S1 and S2):							
Pin	Signal	Pin	Signal	Pin	Signal	Pin	Signal
1	CD	4	DTR	6	DSR	8	CTS
2	RD	5	GROUND	7	RTS	9	RI
3	TD						

✍ ***TECHNICAL SPECIFICATION:***

Compatibility: -PCI 32Bit card for 486/586/Pentium/Pentium-II/P-III/C5/K6

Operating system: -Win 95,98,NT,2000,XP,LINUX
Chips: -1 x SUN1889
Connections: -2 x 9 Pin D-SUB male
connector serial